

hmi

high-accuracy
measurement
instruments

FICHA TÉCNICA DE PRODUTO

PRODUCT DATASHEET

HMI – Automação e Instrumentação, Lda.



Travessa da Indústria, nº 111
4780-573 Santo Tirso
PORTUGAL

Tel. +351 252 850 501
Fax. +351 300 013 487



Web: www.hmi.pt

Email: hmi@hmi.pt

Overvoltage protection for 2-wire fieldbus cable

	NGV210-NO, NGV211-NO	NGV210-EX, NGV211-EX
	 M10838	 M10839
Application	Overvoltage protection device for <u>two</u> separate floating signal circuits (PROFIBUS PA, FOUNDATION Fieldbus-H1 and 4 ... 20 mA HART), consisting of a base element NGV210-NO and a plug-in module NGV211-NO. A fine protection element guarantees a low voltage threshold in conjunction with fast response between the corresponding cores. The high surge arresting capacity is achieved by using gas-filled surge voltage arresters from each wire to the common reference potential.	Overvoltage protection device for <u>two</u> separate intrinsically safe floating signal circuits (PROFIBUS PA, FOUNDATION Fieldbus-H1 and 4 ... 20 mA HART), consisting of a base element NGV210-EX and a plug-in module NGV211-EX. The installation site is Ex zone 1 and 2. The signal circuits may reach into Ex zone 0.
Internet	www.abb.com/fieldbus	www.abb.com/fieldbus
Temperature range	-40 ... 85 °C	-40 ... 85 °C
Inflammability class in acc. with UL 94	V0	V0
Type of protection	IP 20	IP 20
Approval	UL/cUL Listed, cULus Recognized, GOST, GL	UL/cUL Listed, cULus Recognized, GOST, ATEX, IECEx, BR-Ex
Explosion protection	-	II 1G Ex ia IIC T4 ... T6 Ga, II 1D Ex ia IIIC T135°C...T85°C Da
FISCO approval	-	Not for passive components
Physics	MBP-LP, IEC 61158, 2-wire	MBP-IS, IEC 61158, 2-wire
Nominal voltage U_N	24 V AC	24 V DC
Max. permitted voltage U_C	40 V DC / 28 V AC	30 V DC / 21 V AC
Direct lightning impulse current I_{imp} (10/350) μ s	Per path: 2,5 kA	Core-Core: 1 kA
Nominal current I_N	Max. 450 mA (45 °C)	Max. 325 mA (40 °C)
Nominal discharge surge current I_N (8/20) μ s	Core-core / core-(PE): 10 kA / 10 kA	Core-core / core-(PE): 10 kA / 10 kA
Max. discharge current I_{max} (8/20) μ s	20 kA	20 kA
Output voltage limitation at 1 kV/ μ s	Core-core / core-(PE): ≤ 55 V / ≤ 450 V	Core-core / core-(PE): ≤ 45 V / ≤ 1 kV
Residual voltage	Core-core: ≤ 55 V	Core-core: ≤ 45 V
Response time t_A	Core-core / core-(PE): ≤ 1 ns / ≤ 100 ns	Core-core / core-(PE): ≤ 1 ns / ≤ 100 ns
Resistance per path	1-2 / 5-6 / 7-8 / 11-12: 2.2 Ω \pm 10 %	2.2 Ω \pm 10 %
Base element	For mounting on top hat rail, with gas-filled surge arrester between connections 3/4 (PE) and 9/10	For mounting on top hat rail
Base element and plug-in module	2-channels	2-channels
Total dimension	W / H / L: 17.7 / 65.5 / 90 mm	W / H / L: 17.7 / 65.5 / 90 mm
Connection data for cable: solid / stranded / AWG	0.2 ... 4 mm ² / 0,2 ... 2.5 mm ² / 24 ... 12	0.2 ... 4 mm ² / 0.2 ... 2.5 mm ² / 24 ... 12

Surge protection for 2-wire fieldbus cable

	NGV220-NO	NGV220-EX
	 M10840	 M10841
Application	Surge protection for cable gland mounting (PROFIBUS PA, FOUNDATION Fieldbus-H1 and 4 ... 20 mA HART), M20 x 1.5, standard, 1-channel.	Surge protection for cable gland mounting (PROFIBUS PA, FOUNDATION Fieldbus-H1 and 4 ... 20 mA HART), M20 x 1.5, Ex(Haz.) mounting, 1-channel. Hint: Surge protection is permitted only for ATEX intrinsically safe devices which will be installed in zone 1 or 2. Measuring loop of these devices with surge protection can also be used for zone 0 if allowed in the ATEX approval of this device type.
Internet	www.abb.com/fieldbus	www.abb.com/fieldbus
Operating temperature range	-40 ... 80 °C	-40 ... 80 °C
Enclosure material	NIRO V2A	NIRO V2A
Type of protection	IP 67	IP 67
Approvals	CE, EAC, SIL	CE, EACEx, ATEX, IECEx, SIL
Explosion protection	–	ATEX: II 2(1)G Ex ia [ia Ga] IIC T4 ... T6 Gb
FISCO approval	–	Not for passive components
Physics	MBP-LP, IEC 61158, 2-wire	MBP-IS, IEC 61158, 2-wire
Nominal voltage U_N	24 V	24 V
Max. continuous voltage U_C	34.8 V DC / 24.5 V AC	34.8 V DC / 24.5 V AC
Max. U_i / I_i (Input) acc. to EN 60079-11	–	30 V / 0.5 A
Capacitance	Core-core/core-PG: ≤ 400 pF / ≤ 20 pF	Core-core/core-PG: ≤ 850 pF / ≤ 15 pF
Nominal current I_N	0.5 A	0.5 A
C2 Nominal discharge current I_N (8/20) μ s	Total / per core: 10 kA / 10 kA	Total / per core: 10 kA / 5 kA
C2 Nominal discharge current I_N (8/20) μ s	shielding-PG: 20 kA	–
Voltage protection level at 1 kV/ μ s C3	Core-core / core-PG: ≤ 50 V / ≤ 500 V	Core-core / core-PG: ≤ 49 V / ≤ 1 kV
Voltage protection level at I_N C2	Core-core / core-PG: ≤ 65 V / ≤ 650 V	Core-core / core-PG: ≤ 55 V / $\leq 1,1$ kV
D1 Lightning impulse current I_{imp} (100/350 μ s)	Per line: 1 kA	Per line: 1 kA
Series impedance per line	2.2 Ω	1.8 Ω
Mounting of field / connection	M20 x 1.5 female thread / screw	M20 x 1.5 female thread / screw
Mounting of device side / connection	M20 x 1.5 male thread / connecting leads 1.5 mm ² , length 200 mm	M20 x 1.5 male thread / connecting leads 1.5 mm ² , length 200 mm
Total dimension	W / H / L: 27 / 71 / 27 mm	W / H / L: 27 / 71 / 27 mm
Cross-section area for field: solid / flexible	0.08 ... 2.5 mm ² / 0.08 ... 1.5 mm ²	0.08 ... 2.5 mm ² / 0.08 ... 1.5 mm ²
Grounding by	Enclosure	Enclosure

Fieldbus accessories

Ordering Information

Overvoltage protection for 2-wire fieldbus cable (PROFIBUS PA, FOUNDATION Fieldbus-H1)		Catalog No.
NGV210-NO (2839224) For 2-wire fieldbus cable (PROFIBUS PA, FOUNDATION Fieldbus-H1, 4 ... 20 mA HART) Overvoltage protection - Basic element for NGV211-NO with gas conductor top-hat rail mounting, IP 20, 2-channel		9890180
NGV211-NO (2838283) For 2-wire fieldbus cable (PROFIBUS PA, FOUNDATION Fieldbus-H1, 4 ... 20 mA HART) Overvoltage protection - Cartridge for signal loops operated at zero ground potential, IP 20, 2-channel U_N 24 V AC, $I_N \leq 450$ mA		9890181
NGV210-EX (2839279) For 2-wire fieldbus cable (PROFIBUS PA, FOUNDATION Fieldbus-H1, 4 ... 20 mA HART) Overvoltage protection - Basic element for NGV211-EX for the Ex (Haz.) area top-hat rail mounting, IP 20, 2-channel		9890182
NGV211-EX (2838225) For 2-wire fieldbus cable (PROFIBUS PA, FOUNDATION Fieldbus-H1, 4 ... 20 mA HART) Overvoltage protection - Cartridge for Ex ia circuits, IP 20, 2-channel U_N 24 V DC, $I_N \leq 325$ mA		9890183
NGV220-NO (929941) (Note 1) For 2-wire fieldbus cable (PROFIBUS PA, FOUNDATION Fieldbus-H1, 4 ... 20 mA HART) Surge protection for cable gland mounting, M20 x 1.5, IP 67, 1-channel U_N 24 V DC, $I_N \leq 500$ mA		7964116
NGV220-EX (929960) (Note 1) For 2-wire fieldbus cable (PROFIBUS PA, FOUNDATION Fieldbus-H1, 4 ... 20 mA HART) Surge protection for cable gland mounting, M20 x 1.5, for Ex ia circuits, IP 67, 1-channel U_N 24 V DC, $I_N \leq 500$ mA, Hint: Surge protection is permitted only for ATEX <u>intrinsically safe</u> devices which will be installed in zone 1 or 2. Measuring loop circuit of these devices with surge protection can also be used for zone 0 if allowed in the ATEX approval of this device type.		7964115

Note 1: Not suitable for field device types with low lying M20 x 1.5 thread! Note NGV220 outer dimensions!
 Option: Insert M20 x 1,5 / M20 x 1,5 intermediate support.

Notes

Notes

Notes

Contact us

ABB Automation GmbH

Service Instrumentation

Kallstadter Straße 1

68309 Mannheim, Germany

Customer service center: +49 (0)180 5 222 580*

E-Mail: automation.service@de.abb.com

www.abb.com/measurement

* 14 cents/minute from German landlines,
max. 42 cents/minute from mobiles.

Note

We reserve the right to make technical changes or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. ABB does not accept any responsibility whatsoever for potential errors or possible lack of information in this document.

We reserve all rights in this document and in the subject matter and illustrations contained therein. Any reproduction, disclosure to third parties or utilization of its contents - in whole or in parts - is forbidden without prior written consent of ABB.

Copyright© 2017 ABB

All rights reserved

3KXN515000R1001













Sales



Service



Our offering:

 <p>Actuators and Positioners</p>	 <p>Analytical Instruments</p>
 <p>Device Management, Fieldbus and Wireless</p>	 <p>Flow Measurement</p>
 <p>Force Measurement</p>	 <p>Level Measurement</p>
 <p>Natural Gas Measurement</p>	 <p>Pressure Measurement</p>
 <p>Recorders and Controllers</p>	 <p>Temperature Measurement</p>

HMI – Automação e Instrumentação, Lda.

Travessa da Indústria, nº 111
4780-573 Santo Tirso
PORTUGAL

Tel. +351 252 850 501
Fax. +351 300 013 487

Web: www.hmi.pt

Email: hmi@hmi.pt